




Call4Tel FXS Gateway Configuration Manual

INDEX

STEP 1: CONNECT LAN PORT AND POWER ADAPTER	2
STEP 2: 3CX MANAGEMENT CONSOLE CONFIGURATION	2
STEP 3: CALL4TEL FXS GATEWAY CONFIGURATION	6
STEP 4: 3CX REGISTRATION VERIFICATION	8

STEP 1: CONNECT LAN PORT AND POWER ADAPTER


1. LAN Ports
2. Reset Button
3. Power (On/Off Switch), once turned on, a green light will appear in PWR
4. AC Adapter Port



STEP 2: 3CX MANAGEMENT CONSOLE CONFIGURATION

2A. Adding FXS

Login to your 3CX Management Console, go to the Advanced Tab --> FXS/DECT



2B. Click on + Add FXS / DECT

Add FXS/DECT

Select Brand
Call4tel

Select model/device
16 Port FXS gateway

Mac Address
Mac Address

- 12 Port FXS gateway
- ✓ 16 Port FXS gateway
- 2 Port FXS gateway
- 24 Port FXS gateway
- 32 Port FXS gateway
- 4 Port FXS gateway
- 8 Port FXS gateway

OK Cancel

Select Brand	Call4tel
Select Model / Device	The device purchased
Mac Address	Can be found on the device

2C. Device Added in 3CX

Once the device is added, click on the "Extension Tabs" to configure the port according to the extension.

3CX

Support Updates

Call4tel NX-S16 OK Cancel

General Extensions

FXS/DECT Details

Enter name for Device
Call4tel NX-S16

Provisioning Method
Local LAN (in the office)

Provisioning Link: <http://172.16.8.236:5000/provisioning/b1ddpkpqsxj/388ACD600959-ExtensionConfig.xml>

Mac Address
388ACD600959


Select Interface
172.16.8.236

Language
English

2D. Extension Synchronization

Synchronize the extension in the FXS Gateway according to the port.


Note: Ensure that there are no duplicate extension numbers during configuration




Click on "OK" to save the setting.

2E. Generating the XML File


Click on the configured device



Click on the Provisioning Link



You will now be directed to the XML file as shown below:



Save (CTRL+S) the XML file to configure the device on the next step.


STEP 3: CALL4TEL FXS GATEWAY CONFIGURATION

3A. Login to Call4Tel Gateway Device

Login URL: XXX


Username: root

Password: 3cx




3B. Upload XML File to the device

Go to System Tab --> Tools --> Upload Configuration --> Select File (Shown in step 2E) --> Upload Icon




3C. Checking Port Status

You may check the Port Status by going to System Tab --> Status --> Port Status



3D. Checking Extension Register Status

You may check the Port Status by going to System Tab --> Status --> Register Status



The device port shall be lit in green upon successful configuration.



STEP 4: 3CX REGISTRATION VERIFICATION

Login to your 3CX management console navigate to the "Users" tab to check the 3CX registration status

	Ext.	First Name	Last Name
<input type="checkbox"/>	100	admin	admin
<input type="checkbox"/>	101		
<input type="checkbox"/>	102		
<input type="checkbox"/>	103		
<input type="checkbox"/>	104	Yealink TEST	
<input type="checkbox"/>	105		
<input type="checkbox"/>	106		
<input type="checkbox"/>	107		
<input type="checkbox"/>	108		
<input type="checkbox"/>	109		